



100 Hancock Ave  
Hamilton, Ohio 45011

www.jetstream-usa.com  
800-524-4889

# Instructions for JTPS28



## Specifications:

28 amp surge, 25 am continuous

4 lbs

Compact 7" w x 2 1/4" h x 8" d

Over current protection

Over voltage protection

Quiet internal cooling fan

Switchable input voltage 110VAC or 220VAC. Factory set to 110VAC

Works with AC input from 85-135VAC or 170-260VAC

AC line fuse 6 amps

## Installation:

**Before plugging the JTPS28 into an AC outlet make sure that the proper input voltage is selected on the rear of the unit. Select 115 for 110-120V and 230 for 200-240V operation. The JTPS28 is factory set for 115V.**

Loads can be connected to the binding post on the front, the back or the cigarette lighter plug. You may use as many of these as you like at the same time as long as you do not exceed the maximum rating of 25 amps. The cigarette lighter plug and binding posts on the back are limited to 7 amps. If you are using more than 7 amps, you must use the binding posts on the front.

## Operation:

The JTPS28 has a fixed output of 13.8 VDC. You do not need to adjust the voltage output.

The fan will run at low speed when the unit is turned on. The fan speed will automatically adjust as needed.

## Warranty:

The JTPS28 has a 1 year warranty from date of purchase for manufactures defects. The warranty is only valid for the original owner and must be purchased from an authorized Jetstream dealer. The purchaser must supply proof of purchase.

Jetstream is not responsible for any shipping charges. Purchaser must pay all shipping charges for warranty repair.

This does not cover any kind of abuse. This also only covers the JTPS28, it does not cover any device that is hooked up to it. Warranty is void if the voltage switch is set to the wrong position. Warranty is void if the JTPS28 comes in contact with water. Warranty is void for owners who attempt to repair/modify the JTPS28.

**www.jetstream-usa.com 800-524-4889**